



# PRESIDENCY UNIVERSITY

BENGALURU

Roll No.																			
----------	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--

## Make Up Examinations - December 2025

Date: 26 - 12- 2025

Time: 9:30am - 12:30pm

School: SOE	Program: B.Tech		
Course Code : ECE3002	Course Name: DIGITAL SIGNAL PROCESSING		
Semester: MK	Max Marks:100	Weightage: 50%	

CO - Levels	C01	C02	C03	C04	C05
Marks	24	24	26	26	NA

### Instructions:

- (i) Read all questions carefully and answer accordingly.
- (ii) Do not write anything on the question paper other than roll number.

### Part A

Answer ALL the Questions. Each question carries 2marks.

10Q x 2M=20M

1.	Using matrix method obtain the circular convolution of the sequences $x(n) = \{1, 2, -1, 1\}$ and $h(n) = \{2, 4, 6, 8\}$	2 Marks	L2	C01
2.	Perform the linear convolution for the same sequence given in Ques.no:1	2 Marks	L2	C01
3.	Draw the basic butterfly diagram of radix 2 DIF FFT method.	2 Marks	L2	C02
4.	Calculate the multiplication reduction factor or percentage of saving, $\alpha$ in computing 1024 point DFT, is a radix-2 FFT algorithm	2 Marks	L3	C02
5.	Find the digital transfer function $H(z)$ by using impulse invariant method for the analog transfer function $H(s) = 1/s+2$ . Assume $T=0.1$ sec	2 Marks	L2	C03
6.	Give any two properties of Butterworth filter and Chebyshev filter.	2 Marks	L1	C03
7.	Write the magnitude function of Butterworth filter. What is the effect of varying order of N on magnitude and phase response?	2 Marks	L1	C03
8.	Write the linear phase condition for a FIR Filter.	2 Marks	L1	C04
9.	Determine the transversal structure of the system function $H(z)=1+2z^{-1}-z^{-2}-3z^{-3}$	2 Marks	L2	C04
10.	What are the desirable and undesirable features of FIR filter?	2 Marks	L1	C04

## Part B

### Answer the Questions.

**Total Marks 80M**

<b>11.</b>	<b>a.</b>	Implement the linear convolution of given sequences $x(n) = \{1, 2, 3, -1, -2, -3, 4, 5, 6\}$ and $h(n) = \{2, 1, -1\}$ using the Overlap-Add method and compare the result with linear convolution.	<b>10 Marks</b>	<b>L3</b>	<b>CO1</b>
	<b>b.</b>	An analog signal $x(t) = 5\sin(600\pi t) + 4\cos(800\pi t) + 2\sin(1200\pi t)$ a) Calculate the minimum sampling rate required to sample the signal without aliasing. b) Discuss the effects of sampling the signal at 1000 Hz and 400 Hz.	<b>10 Marks</b>	<b>L3</b>	<b>CO1</b>
<b>Or</b>					
<b>12.</b>	<b>a.</b>	Obtain the convolution of the sequences $x(n) = \{3, -1, 0, 1, 3, 2, 0, 1, 2, 1\}$ and $h(n) = \{1, 1, 1\}$ using Overlap save method and compare the result with Linear convolution.	<b>10 Marks</b>	<b>L3</b>	<b>CO1</b>
	<b>b.</b>	Compute the sequence $x_3(n)$ obtained from the circular convolution of $x_1(n) = \{1, 2, 2, 1\}$ and $x_2(n) = \{1, 2, 3, 4\}$ using the Discrete Fourier Transform and its inverse DFT.	<b>10 Marks</b>	<b>L3</b>	<b>CO1</b>
<b>13.</b>	<b>a.</b>	Compute the eight point DFT of the sequence $x(n) = \{1, 1, 1, 1, 1, 1, 0\}$ using radix2 decimation in frequency. Follow exactly the corresponding signal flow graph and keep track of all the intermediate quantities by putting them on the diagram.	<b>15 Marks</b>	<b>L3</b>	<b>CO2</b>
	<b>b.</b>	Compute the IDFT of sequence $X(K) = \{10, -2+2j, -2, -2-2j\}$ using Radix 2 - DIF algorithm.	<b>5 Marks</b>	<b>L3</b>	<b>CO2</b>
<b>Or</b>					
<b>14.</b>	<b>a.</b>	Examine the 8-point DFT of the sequence $x(n) = n$ ; using DIT- FFT algorithm. Illustrate with a neat butterfly diagram	<b>15 Marks</b>	<b>L3</b>	<b>CO2</b>
	<b>b.</b>	Find the IDFT of the sequence $X(K) = \{3, -j, 1, j\}$ using Radix 2 -DIT algorithm.	<b>5 Marks</b>	<b>L3</b>	<b>CO2</b>
<b>15.</b>	<b>a.</b>	Draw the magnitude response of type I and II Chebyshev filter and obtain the steps for designing an analog Chebyshev filter.	<b>10 Marks</b>	<b>L2</b>	<b>CO3</b>
	<b>b.</b>	Using Impulse Invariant method find the transfer function of the digital filter for $H(s) = \frac{10}{s^2 + 7s + 10}$ for $T = 0.2$ Sec.	<b>10 Marks</b>	<b>L2</b>	<b>CO3</b>
<b>Or</b>					
<b>16.</b>	<b>a.</b>	Design and analyse a digital butter worth filter satisfying the constraints $0.707 \leq  H(\omega)  \leq 1$ ; $0 \leq \omega \leq \frac{\pi}{2}$ $ H(\omega)  \leq 0.2$ ; $\frac{3\pi}{4} \leq \omega \leq \pi$ With $T = 1$ sec using bilinear transformation .	<b>20 Marks</b>	<b>L4</b>	<b>CO3</b>
<b>17.</b>	<b>a.</b>	Design a low pass filter using rectangular window by taking 9 samples of $w(n)$ and cut off frequency of 1.2 rad/sec and realise the same using suitable structure.	<b>20 Mark</b>	<b>L3</b>	<b>CO4</b>
<b>Or</b>					
<b>18.</b>	<b>a.</b>	Design a high pass filter of length $N = 11$ and cutoff frequency of 0.5Hz and Sampling rate of 2KHz using Hamming window and realise the same using suitable structure.	<b>20 Marks</b>	<b>L3</b>	<b>CO4</b>