



PRESIDENCY UNIVERSITY

BENGALURU

Roll No.																			
----------	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--

End - Term Examinations - December 2025

Date: 15-12-2025

Time: 1.00pm to 04.00pm

School: SOCSE	Program: B.Tech		
Course Code: IST2503	Course Name: Deep Learning Techniques		
Semester: V	Max Marks: 100	Weightage: 50%	

CO - Levels	CO1	CO2	CO3	CO4	CO5
Marks	26	24	24	26	-

Instructions:

- (i) Read all questions carefully and answer accordingly.
- (ii) Do not write anything on the question paper other than roll number.

Part A

Answer ALL the Questions. Each question carries 2marks.


10Q x 2M=20M

1.	Define Deep Learning? List out the applications of Deep Learning.	2 Marks	L1	CO1
2.	What is an Activation Function? List any 2 activation functions	2 Marks	L1	CO1
3.	Outline a NN with 2 Input neurons and 2 hidden layers each with 3 Neurons and 1 output layer with 2 neurons	2 Marks	L1	CO1
4.	Define Regularization and list its strategies.	2 Marks	L1	CO2
5.	Define overfitting and underfitting the model.	2 Marks	L1	CO2
6.	List the applications of RNN.	2 Marks	L1	CO3
7.	Define Padding with example.	2 Marks	L1	CO3
8.	Define Restricted Boltzman machine.	2 Marks	L1	CO4
9.	List the different types of Autoencoders.	2 Marks	L1	CO4
10.	Define GAN.	2 Marks	L1	CO4


Part B

Answer the Questions.

Total Marks 80M

11.	a.	Explain in detail: 1. Sigmoid Activation Function 2. Leaky ReLU/Parametric ReLu.	10 Marks	L2	C01
	b.	 <p>Solve the given NN using Back Propagation, use Sigmoid activation function for the hidden and output layer. Take learning rate=0.01. Update the weight w_3 and bias b_2 for one iteration.</p>	10 Marks	L3	C01

Or

12.	a.	 <p>Solve the given NN using Back Propagation, use Sigmoid activation function for the hidden and output layer. Take learning rate=0.01. Update the weight w_3 and bias b_2 for one iteration.</p>	10 Marks	L3	C01
	b.	Explain in detail the perceptron Neural Network with respect to Forward propagation	10 Marks	L2	C01

13.	a.	Explain Batch Normalization with an example.	10 Marks	L2	C02
	b.	Explain the methods /approaches for hyper parameter tuning.	10 Marks	L2	C02

Or

14.	a.	Explain the following: i) Learning rate ii) L1 Norm Regularization iii) L2 Norm Regularization	10 Marks	L2	C02
-----	----	--	----------	----	-----

	b.	Explain overfitting and underfitting the model.	10 Marks	L2	CO2
--	-----------	---	-----------------	-----------	------------

15.	a.	Explain with a neat diagram the convolutional neural network architecture in detail.	10 Marks	L2	CO3
------------	-----------	--	-----------------	-----------	------------

	b.	Assume $x_t=0.1$, $h_{t-1} = 0.2$, $C_{t-1} = 0.35$, Weights and biases: Input gate: $W_i=0.25$, $U_i=0.1$, $b_i=0.1$, Forget gate: $W_f=0.1$, $U_f=0.3$, $b_f=0.5$, Cell state: $W_c=0.1$, $U_c=0.4$, $b_c=0.2$, Output gate: $W_o=0.5$, $U_o=0.1$, $b_o=0.2$. Compute all the LSTM gates for the given date.	10 Marks	L4	CO3
--	-----------	---	-----------------	-----------	------------

Or

16.	a.	Explain with diagram how do the gates in GRU work together to regulate information flow?	10 Marks	L3	CO3
------------	-----------	--	-----------------	-----------	------------

	b.	Assume $x_t=0.5$, $h_{t-1} = 0.4$, $C_{t-1} = 0.3$, Weights and biases: Input gate: $W_i=0.2$, $U_i=0.3$, $b_i=0.11$, Forget gate: $W_f=0.5$, $U_f=0.4$, $b_f=0.2$, Cell state: $W_c=0.3$, $U_c=0.2$, $b_c=0.1$, Output gate: $W_o=0.4$, $U_o=0.3$, $b_o=0.1$. Compute all the LSTM gates for the given date.	10 Marks	L4	CO3
--	-----------	--	-----------------	-----------	------------

17.	a.	Explain the architecture of Autoencoder in detail.	10 Marks	L2	CO4
------------	-----------	--	-----------------	-----------	------------

	b.	Construct KSOFM cluster for the given data: Input vectors: [0 0 1 1], [1 0 0 0],[0,1,1,1],[0,0,0,1] Number of clusters: 2 Learning rate: 0.5 Initial Weight Matrix is given as : Unit 1=[0.2,0.3,0.4,0.6] and Unit2=[0.5,0.6,0.7,0.3].	10 Marks	L3	CO4
--	-----------	--	-----------------	-----------	------------

Or

18.	a.	Construct Hopfield Neural Network for the Input pattern: 11011, 10101. calculate weight matrix and find correct pattern of distorted pattern (11110) for the sequence: 5 3 4 1 2	10 Marks	L3	CO4
------------	-----------	--	-----------------	-----------	------------

	b.	Explain in detail the architecture of GAN.	10 Marks	L2	CO4
--	-----------	--	-----------------	-----------	------------